

---

# Accessory

## Compensator

---

**Type:** 6596

**Product ID:** 2CKA006599A2290

**GTIN:** 4011395638507



Prevents the self-ignition of energy-saving or LED lamps during switching with orientation illumination (parallel to the lamp). Prevents after-glow of low-voltage halogen or LED lamps in a deactivated state due to possible ripple voltage or activation via touch-dimmer without neutral conductor connection (parallel to the primary transformer side or to the lamp). Removes noise generation on electronic transformers in a switched-off state during activation via touch-dimmer without neutral conductor connection (parallel to the primary transformer side). Removes ripple voltages on the control line in blind control/group controls (parallel between control wire "UP" and neutral conductor as well as "Down" and neutral conductor). Dimensions: diameter 22 mm, length 25 mm, length of the connecting cable approx. 235 mm. Rated voltage: 250 V~ Rated frequency: 50 Hz

## Technical specification

### Packing

|          |      |
|----------|------|
| Package: | 1/10 |
| Unit:    | PCS  |

### ETIM Data

|             |    |
|-------------|----|
| Accessory:  | No |
| Spare part: | No |