
Button / Buzzer

Button / Buzzer, 1-fold

Type: FIP1011

Product ID: 2TKA00003793

GTIN: 6438199005225



A device including a push button as well as a buzzer. The LED of the push button and the buzzer operates in parallel. The buzzer can be cancelled with the push button. When cancelled the LED remains on till the alarm goes off. Good marking possibilities on the push button and the name plate. Operating voltage 9,5 - 28 Vac / 9,5 - 35 Vdc. Current consumption: 45 mA ac / 25 mA dc. Load capacity of the switch: 30 Vac / 35 Vdc, 100 mA ac/dc, 3 VA / 3 W.

Technical specification

Signal products

| | |
|-----------------------------------|---------------------------------|
| Sound frequency: | 400 Hz, 70 dB / 30 cm |
| Loading capacity of switch (max): | 100 mA ac/dc, 30 V ac / 35 V dc |

Electrical quantities

| | |
|----------------------|-------------------------------|
| Operating voltage: | 9,5 - 28 V ac / 9,5 - 35 V dc |
| Current consumption: | 45 mA ac / 25 mA dc |

Packing

| | |
|----------|---------------|
| Package: | 1/10/100/1200 |
| Unit: | PCS |

Product Card

Button / Buzzer, 1-fold



ETIM Data

| | |
|----------------|-------|
| Device width: | 71 mm |
| Device height: | 39 mm |
| Device depth: | 71 mm |