# Switch insert

1-gang intermediate switch insert, 16AX/250V, 2 X-terminals, lamp possibility

**Type:** 1067.21

Product ID: 2TKA000201G1

GTIN: 6418677328664



7-switch insert without rocker. All 1-gang rockers are suitable for the insert except 1788-xx. The switch has switch-over insert and 2 X-terminals. The X-terminals can be used for extending other wires. A signal light can be connected.

## **Technical specification**

### **Electrical quantities**


Nominal voltage:	250 V	
Rated current:	16 AX	
Classification		
Suitable for degree of protection (IP):	IP21	
Packing		
Package:	10/100	
Unit:	PCS	
ETIM Data		

Customer service puh. +358 10 222 1999 contact.center@fi.abb.com

### ABB Exchange

+358 10 22 11







### **Product Card** 1-gang intermediate switch insert, 16AX/250V, 2X-terminals, lamp possibility



Wiring system:	Other
Method of operation:	Rocker/button
Assembly arrangement:	Basic element with full cover plate
Push button switch:	No
Number of rockers:	1
Mounting method:	Surface mounted (plaster)
Type of fastening:	Mounting with claw and screw
With mounting plate:	No
Material:	Plastic
Material quality:	Thermoplastic
Halogen free:	Yes
Anti-bacterial treatment:	No
Surface protection:	Galvanized
Colour:	Stainless steel
RAL-number (similar):	9010
Label space/information surface:	No
Illumination:	No
Rated current:	16 A
Switching current for fluorescent lamps:	16 AX
Feedback-signal contact:	No
Connection type:	Other
Washing machine switch:	No
Device width:	70 mm
Device height:	35 mm
Device depth:	85 mm
Built-in depth:	18 mm
Min. depth of built-in installation box:	18 mm

\_

Customer service

puh. +358 10 222 1999 contact.center@fi.abb.com

####